CT198N

SPECIFICATIONS





0,75" NEO Dome Tweeter


Program Power Rated impedance Nominal diameter Sensitivity (1W/1m) Voice coil diameter **Frequency Range**

100 W 4 Ohm 0,75"- 20 mm 90 dB 0,78 in - 19 mm 5000-20000 Hz

FREQUENCY RESPONSE AND IMPEDANCE CURVE 67

Nominal Diameter		0,75"- 20 mm	
Rated Impedance		4 Ohm	
Nominal Power Handling 1		50 W	
Program Power ²		100 W	
Sensitivity ³		90 dB	
Frequency Range ⁴		5000-20000 Hz	
Minimum Impedance		-	
Flange material		-	
Magnet Material		Neodymium	
Diaphragm Material		Silk	
Diaphragm Shape		Dome	
Surround		-	
Voice Coil Diameter		0,78 in - 19 mm	
Voice Coil Winding Material		-	
Voice Coil Former Material		Kapton	
Flux Densitry		-	
Ferrofluid		Yes	
Connection type		-	
Recommended Crossover Frequency		-	
Alternative Available Version	8 Ohm	HT198N	

+110 AD +105 +100 +95 +9 d B r Ch +8 +8 +7(+70 +62 Hz



T/S PARAMETERS

Resonance frequency	Fs	1450 Hz
DC Resistance	Re	3,2 Ohm
Mechanical Q Factor	Qms	1,93
Electrical Q Factor	Qes	5,24
Total Q Factor	Qts	1,41
BI Factor	BI	1 Tm
Effective Moving Mass	Mms	0,15 g
Suspension Compliance	Cms	-
Effective Piston Diameter	D	23 mm - 0,91 in
Effective piston area	Sd	4 cm² - 0,62 sq in
Voice Coil Inductance @ 1kHz	Le	0,04 mH

MOUNTING AND SHIPPING INFORMATION

Overall Diameter	37 mm - 1,46 in
Baffle Cutout Diameter	33 mm - 1,3 in
Flange Thickness	4,5 mm - 0,18 in
Total Depth	19,5 mm - 0,77 in
Bolt Circle Diameter	
Bolt Holes Quantity and Diameter	- /
Net Weight	0,06 Kg - 0,13 lb
Shipping Units	6 Pairs

NOTES

¹ Nominal power is determined according to AES2-1984 (r2003) standard.
² Program Power is defined as 3 dB greater than the Nominal rating.

³ Sensitivity represents the averaged value of acoustic output as measured on the forward central axis of cone, at distance 1m, when connected to 2,83V sine wave test signal.

⁴ Frequency range is given as the band of frequencies delineated by the lower and upper limits where the output level drops by 10 dB below the rated sensitivity in half space environment. ⁶ Frequency response curve is measured on IEC Baffle.

⁷ Impedance curve is measured in free air conditions at small signals.

4 Ohm